



Maretti Lighting | 1332 AX Almere | T +31 (0) 36 532 66 12 | E info@maretti.com
Bolderweg 7 | the Netherlands | W www.maretti.com

Maretti Lighting is well-known in the World of interior design. In businesses, homes, store chains, and hospitality facilities all over the world, Maretti is unmistakable present with its project lighting that does more than just provide light. We make lighting an essential part of the interior. Maretti stands for stylish top quality and trendsetting design, modern, timeless and most of all, original.

Maretti Lighting works with all the top brands in the lighting industry, but we are especially notable for our own large product line and introduce our own brand name "Maretti". Our production team distinguishes itself time and time again with unique innovations from our own atelier and therefore our projects exude an entirely unique identity.

© Copyright Maretti Projectverlichting.

Our IM was made with the greatest of care. Nevertheless, the colours displayed in the IM may differ slightly from the real colours because of the printing process. Colour, size and range are subject to change. Nothing from this IM may be copied, reproduced and/or published by print, photocopy or in any other way without Maretti Lighting's written permission. All product and design copyrights belong to Maretti Lighting.

GUARANTEE TERMS AND CONDITIONS

The other party should inspect the delivered items immediately upon receipt with regard to its soundness. Entitlements to repair or replacement only exist if the other party

- In the case of visible defects, informs MPV of them immediately.

- In the case of defects that are not visible, informs MPV in writing of the defects, within 2 working days after the day the defects were found, or in all reason could have been found and furthermore demonstrates that the MPV instructions for use, maintenance and operation were followed, whilst the defects are not the consequence of normal wear and tear, misuse, negligence, accident, exceeding the limits prescribed by the MPV or by the legal safety regulations, or, in the case of a repair or change without MPV's consent or the consent of its recognised repairer, there will be no entitlement to repairs or replacement. The parts that have to be replaced must be made available free of charge to MPV. Noncompliance by the other party to one or more of its obligations will release MPV of all its guarantee obligations. In the case of assembly of the other party's own products by Maretti, MPV will release itself from all guarantee stipulations.


Moreover, our general delivery terms and conditions are applicable. These can be obtained from Maretti or can be downloaded from www.maretti.com

The installation must be done by a competent installer. Maretti recommends that your (outside) lighting and fixtures are inspected and maintained annually.

D: Für Garantiebedingungen bitte lesen Sie unsere Webseite | www.maretti.com
E: Consulte nuestro sitio web para los condiciones de garantia | www.maretti.com
FR: Consultez notre site web pour les conditions de garantie | www.maretti.com
NL: Voor garantievooraardien zie onze website | www.maretti.com

21.8420.82

CARACAS 35 LED MODULE CTA



ZIE OMMEZIJDE VOOR MEER INFORMATIE / SEE BACK SIDE FOR MORE INFORMATION

DC 18V	VOLTAGE	2 pins	FITTING PLUG & PLAY	 DEGREE BEAM ANGLE 24°	-30~+40°C	ENVIRONMENT TEMPERATURE		
6,3W	WATTAGE	420 lm	LUMEN	99-99.5%	LUMEN MAINTENANCE		CE MARK	
	LED MODULE		CTA DIM. 2000-2700K	50.000 hours	LED NOMINAL LIFETIME*			
350 mA	MILLIAMPERE	Ra95	CRI	<0,5s	LAMP WARM UP TIME			

CARACAS 35 LED MODULE CTA

INFORMATION



E: Europlug
G: GST18
W: Winsta
Z: Geen plug


***Nominale levensduur LED:** De gebruiksomstandigheden hebben een grote invloed op de levensduur. Belangrijke factoren: omgevings-temperatuur, schakelfrequentie, vochtigheid, trillingen en spanning.

***LED Nominal Lifetime:** Usage conditions greatly impact lifespan. Key factors: ambient temperature, switching frequency, humidity, vibrations, and voltage.



MARETTI LIGHTING

21.8420.82



6
kWh/1000h



2019/2015

DRIVERS ZIJN APART VERKRIJGBAAR / SEPARATE ORDER

ARTI. NR.	NAAM / NAME	WATTAGE	MILIAMPER	TYPE DIMMING	AANSLUITING	AANTAL LICHTBRONNEN
16.8103.0350.E	DRIVER P&P 15-21VDC	5,25W – 7,35W	350mA	Leading trailing edge dim.	2m kabel eurostekker	1
16.8103.0350.G	DRIVER P&P 15-21VDC	5,25W – 7,35W	350mA	Leading trailing edge dim.	2m kabel GST18	1
16.8103.0350.W	DRIVER P&P 15-21VDC	5,25W – 7,35W	350mA	Leading trailing edge dim.	2m kabel WINSTA	1

DRIVERS ZIJN APART VERKRIJGBAAR / SEPARATE ORDER

ARTI. NR.	NAAM / NAME	WATTAGE	MILIAMPER	TYPE DIMMING	AANSLUITING	AANTAL LICHTBRONNEN
16.7000.0350.G	DRIVER DALI INTEL P&P	0,9W – 10W	350mA	CTA/AM dim.	2m kabel GST18	1
16.7000.0350.W	DRIVER DALI INTEL P&P	0,9W – 10W	350mA	CTA/AM dim.	2m kabel WINSTA	1
16.7000.0350.Z	DRIVER DALI INTEL P&P	0,9W – 10W	350mA	CTA/AM dim.	excl. prim. connector	1

DRIVERS ZIJN APART VERKRIJGBAAR / SEPARATE ORDER

ARTI. NR.	NAAM / NAME	WATTAGE	MILIAMPER	TYPE DIMMING	AANSLUITING	AANTAL LICHTBRONNEN
16.7001.0350.G	DRIVER DALI INTEL P&P	4W – 18W	350mA	AM dim.	2m kabel GST18	2
16.7001.0350.W	DRIVER DALI INTEL P&P	4W – 18W	350mA	AM dim.	2m kabel WINSTA	2
16.7001.0350.Z	DRIVER DALI INTEL P&P	4W – 18W	350mA	AM dim.	excl. prim. connector	2

DRIVERS ZIJN APART VERKRIJGBAAR / SEPARATE ORDER

ARTI. NR.	NAAM / NAME	WATTAGE	MILIAMPER	TYPE DIMMING	AANSLUITING	AANTAL LICHTBRONNEN
16.8101.0350.E	DRIVER P&P 30-42VDC	10,5W – 14,7W	350mA	Trailing edge/triac dim.	2m kabel eurostekker	2
16.8101.0350.G	DRIVER P&P 30-42VDC	10,5W – 14,7W	350mA	Trailing edge/triac dim.	2m kabel GST18	2
16.8101.0350.W	DRIVER P&P 30-42VDC	10,5W – 14,7W	350mA	Trailing edge/triac dim.	2m kabel WINSTA	2

CONNECTION BLOCK FOR 2 CUBA 50 LED MODULE APART VERKRIJGBAAR / SEPARATE ORDER

ART. NR.	NAAM / NAME	INFO.
70.7115.05	CONNECTION BLOCK 3-V SERIES	P&P MALE + 2x70.7120.05 LED BRIDGE

PLUG & PLAY CABLES APART VERKRIJGBAAR / SEPARATE ORDER

ART. NR.	NAAM / NAME	AFMETINGEN / DIMENSIONS
70.7125.05	LED KOPPELKABEL / LED COUPLING CABLE	L: 50cm 2x0,5mm ² mini amp for mA led
70.7127.05	LED KOPPELKABEL / LED COUPLING CABLE	L: 100cm 2x0,5mm ² mini amp for mA led
70.7130.05	LED KOPPELKABEL / LED COUPLING CABLE	L: 150cm 2x0,5mm ² mini amp for mA led



LET OP:

- Volg en bewaar deze gebruiksaanwijzing.
- Zorg ervoor dat de netspanning uitgeschakeld is voor installatie, reparatie of onderhoud.
- (Installatie, reparatie en onderhoud uitsluitend door gekwalificeerde personen).
- Voor reparatie of onderhoud uitsluitend originele delen gebruiken.
- Gebruik het product alleen binnenshuis.

De fabrikant aanvaardt geen enkele aansprakelijkheid voor letsel of schade als gevolg van een verkeerde toepassing van het armatuur. De fabrikant aanvaardt geen garantie in geval van het niet behandelen van de lampen volgens de richtlijnen van de fabrikant. Als er schade aan elektrische onderdelen te vinden zijn, vraag dan een elektricien om het te vervangen.

Onderhoud is behoud:

Een goede instandhouding van het armatuur is sterk afhankelijk van omgevings- en onderhoudsfactoren. Hierop kunnen wij geen invloed uitoefenen.

NOTE:

- Follow and keep this instructions manual.
- Make sure that the mains voltage is switched off for installation, reparation or maintenance. (Installation, reparation and maintenance only by qualified persons).
- Use only original parts for repairs or maintenance.
- Use the product only indoors.

The manufacturer accepts no liability for any injuries or damages resulting from the incorrect use or installation of the fixture. Any operation performed on the fixture that is not in accordance with instructions will void manufacturer's warranty. If you find any damage to the electrical parts, please ask a qualified electrician to replace it.

Maintenance is preservation:

A good preservation of the fixture is highly dependent on environmental factors and maintenance. We cannot exercise any influence on this.

"No rights can be derived from the information provided on this Instruction Manual. Information on the Instruction Manual has been compiled with the utmost care and is updated on a continuous basis. Nevertheless Maretti cannot guarantee that all information is free of errors, complete or fully up to date."